

KGR...H42 Cable Tray

Overview:

Application
Cable routing

Material
Steel, strip-galv. acc. to the Sendzimir method to PN-EN 10346:2011 (SG)

Available to order:
L- powder coating in a full range of colours (PC)







Important! Possibility of joining cable tray sections together through sliding one into another and connector-free assembly. To install cable tray use Screw Sets SGK M6x10 or SG M6x10.

Versions:

Sheet thickness: **0,5 mm**

Symbol	Length L [m]	Width a [mm]	Catalogue number	Quantity in box	Weight [1m]	Effective section
KGR/KPR50H42/2	2000	50	140105	20	0,55	1900
KGR/KPR50H42/3	3000	50	140205	12	0,55	1900
KGR100H42/2	2000	100	141517	12	0,73	4000
KGR100H42/3	3000	100	141516	12	0,73	4000
KGR150H42/2	2000	150	141617	6	0,92	6100
KGR150H42/3	3000	150	141616	6	0,92	6100
KGR200H42/2	2000	200	141717	6	1,10	8200
KGR200H42/3	3000	200	141716	6	1,10	8200
KGR300H42/2	2000	300	141817	6	1,45	12400
KGR300H42/3	3000	300	141816	6	1,45	12400

Connected products:

							
KAJ...H42 Cable Tray	KGL...H42 Cable Tray	KGJ...H42 Cable Tray	KCJ...H42 Cable Tray	KCL...H42 Cable Tray	KOL...H42 Cable Tray	KOJ...H42 Cable Tray	KBR...H42 Cable Tray
							
KBJ...H42 Cable Tray	LPLH42 Straight Connector	LPPH42 Straight Connector	LPMLH42 Straight Connector	LPMPH42 Straight Connector	LGJH42 Articulated Connector	LGPH42 Articulated Connector	LKJH42 Angle Connector
							
KKL...H42 90° Horizontal Bend	KKJ...H42 90° Horizontal Bend	KKBL...H42 90° Horizontal Bend	KKBJ...H42 90° Horizontal Bend	KKML...H42 45° Horizontal Bend	KKMJ...H42 45° Horizontal Bend	KKMBL...H42 45° Horizontal Bend	KKMBJ...H42 45° Horizontal Bend
							
KKPJ...H42 90° Horizontal Bend	KKMPJ...H42 45° Horizontal Bend	TKL...H42 Horizontal Tee	TKJ...H42 Horizontal Tee	TKBL...H42 Horizontal Tee	TKBJ...H42 Horizontal Tee	TKPJ...H42 Horizontal Tee	TKDJ...H42 Add-on Tee
							
LRJH42 Corner Connector	LRBJH42 Corner Connector	RKSL...H42 Straight Reducer	RKSJ...H42 Straight Reducer	RKSBL...H42 Straight Reducer	RKSBJ...H42 Straight Reducer	RKPL...H42 Right Reducer	RKPJ...H42 Right Reducer

